

# DOUBLE TRIODE

# ECC32

Double triode with separate cathodes for use as a paraphase A.F. amplifier and in phase inverters, multi-vibrators, etc.

---

## HEATER

$V_h$	6.3	V
$I_h$	0.95	A

## CAPACITANCES

$C_{a-b}$	0.8	$\mu\mu\text{F}$
$C_{a-g}$ (each section)	4.3	$\mu\mu\text{F}$
$C_{g-k}$ (each section)	4.3	$\mu\mu\text{F}$
$C_{a-k}$ (each section)	2.0	$\mu\mu\text{F}$

## CHARACTERISTICS (each section)

$V_a$	250	V
$V_g$	-4.6	V
$I_a$	6.0	mA
$g_m$	2.3	mA/V
$\mu$	32	
$\Gamma_a$	14	k $\Omega$

---

OPERATING CONDITIONS: 100  $\mu\text{S}$  RESISTANCE CAPACITY COUPLER

# ECC32

## DOUBLE TRIODE

Double triode with separate cathodes for use as a  
paraphase A.F. amplifier and in phase inverters,  
multi-vibrators, etc.

