

## TABLE 2

### PREAMPLIFIER PARTS LIST (ONE CHANNEL)

#### CAPACITORS

	DESCRIPTION	MANUFACTURER/PART #/(SOURCE)
C1	0.1 $\mu$ F	630V Cornell Dubilier (CD) DME6P1k (6,7)
C2, C10, C12	4.7 $\mu$ F, 250V	CD DME2W4P7K (6,7)
C3	0.68 $\mu$ F, 250V	CD DME2P68K (6,7)
C4, C11	1000 $\mu$ F, 10V	Philips (PH) 136.64102 (2)
C5, C9	390pF, 500V mica	CD FD391J03 (6,7)
C6	10,000pF, 5000V mica	CD FD103J03 (6,7)
C7	470pF, 500V mica	CD FD471J03 (6,7)
C8	1200pF, 500V mica	CD FD122J03 (6,7)
C13	1.0 $\mu$ F, 100V	CD DME1W1K (6,7)
C13-22	10 $\mu$ F, 250V	CD DME2W10K (6,7)

#### RESISTORS

R1, R29, R34	1k	PH MRS25 (4)
R2, R9, R28, R35	1M	PH MRS25 (4)
R3, R11	1.8k	PH MRS25 (4)
R4, R32	10k, 25T trimmer	Bourns (BO) 3296W (4,7)
R5	47k	PH MRS25 (4)
R6, R33	100k audio taper cermet	Clarostat L12566 (9)
R7, R10, R39	100k	PH MRS25 (4)
R8	6.8k	PH MRS25 (4)
R14, R18	15k	PH MRS25 (4)
R15, R17	500k linear taper cermet	Clarostat L12565 (9)
R16, R36	120k	PH MRS25 (4)
R36 (6BQ5/EL84 version)	62k	PH MRS25 (4)
R19	500k, 25T trimmer	BO 3296W (293.3k) (4,7)
R20	100k, 25T trimmer	BO 3296W (67.4k) (4,7)
R21	100k, 25T trimmer	BO 3296W (60.4k) (4,7)
R22	50k, 25T trimmer	BO 3296W (49.9k) (4,7)
R23	50k, 25T trimmer	BO 3296W (45k) (4,7)
R24	50k, 25T trimmer	BO 3296W (33k) (4,7)
R25	50k, 25T trimmer	BO 3296W (23k) (4,7)
R26	220k	PH MRS25 (4)
R27	20k, 25T trimmer	BO 3296W (4,7)
R30, R31	510	PH MRS25 (4,7)
R37, R38	75, 3W wirewound, 5%	Ohmite 23J75R (3)
R37, R38 (6BQ5/EL84 version)	120, 3W wirewound, 5%	Ohmite 23J75R (3)
R40	10k, 1W, 5%	Panasonic (3)

#### SWITCHES

S1	2 pole, nonshorting	Electroswitch C3P0212N-A (7)
S2	4 pole, shorting	Electroswitch C3P0406S-A (7)

#### VACUUM TUBES

V1-V3	12AX7	RAM/Chelmer (2,4)
V4, V5	7119/E182CC	Amperex (1,8)
	6BQ5/EL84	Sovtek (1,8)